



Backup and Restoring Presets

This informative document will explain the procedure to quickly backup the presets stored in a module along with the saved system files and also the Latest file. After backing up these presets, you will be able to copy the presets and all the system files to another module so both will be exactly the same in terms of presets and system configurations. This entire process should take no more than 10 minutes to perform.

Steps

1. Backup with Galaxy
2. Restore with Galaxy
3. Make sure everything works

Backing up Presets with Galaxy

1. Connect to the module with saved presets with Galaxy
2. Select Help—Backup All Information
3. This will backup all saved presets and system configuration files to
c:\Avitech_VCC\Backup\VCCH1_1
 - a. Warning: Everything in the Backup folder will be erased, ff

you have previously backed up presets, they will all be written over when you backup presets again, if you want to keep the old presets, please move the entire Backup folder to a temporary directory (e.g. c:\temp)

4. This will create the following directories:
 - a. c:Avitech_VCC\Backup\
 - b. c:Avitech_VCC\Temporary
5. Close Galaxy
 - a. Note: some versions of Galaxy may prompt you to Backup to HDD, if you have done this already you do not need to backup again

Restoring Presets with Galaxy

1. Connect to the module with Galaxy
 - a. Some versions of Galaxy will detect that the module does not have presets and will prompt the user to restore the presets the first time it connects
2. To manually restore the presets, select Help—Restore Module Information
 - a. You should see a progress bar showing the preset being loaded into the machine

3. To complete the backup process, shut down Galaxy and select NO when prompted to save
4. Power cycle the module and then connect with Galaxy and make sure the saved presets are in the flash memory

Technical Support

If you have any questions regarding the information provided in this guide, please call our technical support line at 425-885-3863 or our toll free line at 1-877-AVI-TECH.

To contact the author of this document, please send an email to Thomas@avitechvideo.com.